



**使用范围Application**

QJX2(LC3) 适用于交流50Hz/60Hz, 电压至660V, 电流至95A以下的电路中, 作为电动机的启动装置,它设有定时器, 可出动进行星三角转换, 以降低电动机启动电压及电流。

QJX2(LC3) series star-delta reduced voltage starter is suitable for starting motor in the circuit of AC 50/60Hz,voltage up to 660V and current up to 95A. It is provided with a timer for automatic changeover of star-delta to reduce the voltage and current of motor starting.



QJX2-32



QJX2-65

**主要技术参数 Main Technical Parameter**

型号Type	额定使用电流 Rated operating current (A)	三相电动机电容 3-Phase motor capacity			
		AC3 LOADED			
		220V	380V	415V	440V
QJX2-093		4	7.5	7.5	7.5
QJX2-123	9	5.5	11	11	11
QJX2-183	12	11	18.5	22	22
QJX2-253	17	11	22	22	22
QJX2-323	25	15	25	30	30
QJX2-403	32	18.5	37	37	37
QJX2-503	40	30	55	59	59
QJX2-653	50	32	55	59	59
QJX2-803	65	37	75	75	75
QJX2-953	80	45	80	80	80

电路图  
Wiring Diagram

